Europe / Africa Partners | Where To Buy



PRODUCT NUMBER: 1010928
Thunder T1s Headband
Earmuff

Learn more about our products at howardleight.com

Honeywell HOWARD

Overview

Reference Number

1010928

Product Type

Hearing Protection

Range

Earmuffs

Line

Noise Blocking Earmuffs

Branc

Howard Leight by Honeywell

Brand formerly known as

BILSOM

Industry

- Industry
 Administration
 Agriculture
 Army Defence
 ATEX environment
- Automotive and Part Manufacturer
 Aviation
 Building and Construction
 Catering
- Chemical Industries
 Energy or Electricity
 Fire Protection brigades
 Fishing
 Food Industries
- Foundry Glass Industries Green Spaces Homeland defense Industrial Cleaning
- Iron and steel industry
 Laboratory
 Logistics
 Maintenance
 Medical and Pharmaceutical
- Metal steel
 Minning and Quarrying
 Offshore
 Paper Industries
 Petro-chemical
- Printing Industries Services Ship Building Telecoms Textile Industries Transportation
- Utilities Water treatment Welding Wood Industries

Product Use

Noise Blocking Earmuff

Features & Benefits

Feature

AIR FLOW CONTROL™ TECHNOLOGY Bilsom's patented Air Flow Control™ technology delivers optimal attenuation across all frequencies, without increasing earcup size or weight. A patented baseplate chamber and high-tech non-woven layer manage the flow of air inside the earmuff to control how sound reaches the ear. The result is better, more consistent overall attenuation for virtually all industrial noise environments. Air Flow Control is a standard feature on all Thunder series earmuffs. DIELECTRIC/PLASTIC CONSTRUCTION Thunder's robust nondeforming dielectric

Thunder T1s Headband Earmuff - 1010928

construction withstands use and abuse, while protecting your workers in electrical environments. NON-DEFORMING OUTER HEADBAND Thunder's non-deforming outer headband provides better comfort, minimizes pressure on head, withstanding rough treatment in the toughtest workplaces. QUICK CLICK HEIGHT ADJUSTMENT Height adjustment remains fixed during wear. SNAP-IN EAR CUSHIONS Make replacement quick and easy.

Renefit

When it comes to selecting an earmuff, comfort reigns supreme with workers. That's why the Thunder series earmuff is designed with all-day comfort in mind. Headband earmuffs feature a unique dual-headband for better positioning and breathability, and non-deforming outer headband that minimizes pressure on the head. Plus, its dielectric construction withstands use and abuse, while protecting workers in electrical environments.

Technical Description

SNR (dB)

30

H (dB)

32

M (dB)

28

L (dB)

21

Attenuation Data

Frequency (Hz) Frequenz (Hz) Fréquence (Hz)	63	125	250	500	1000	2000	4000	8000
Mean Attenuation (dB) Mittlere Dämmung (dB) Atténuation moyenne (dB)	16.4	18.3	23.3	26.6	32.9	33.8	36.0	37.9
Standard Deviation (dB) Standardabweichung (dB) Déviation standard (dB)	5.4	4.3	2.7	2.3	2.3	2.9	2.3	3.2
Assumed Protection (dB) Angenommener (dB) Protection supposée (dB)	11.0	14.0	20.6	24.3	30.6	30.9	33.7	34.7

Earmuff Construction

Plastic [or Dielectric]

Other Material

POM, PC/PBT, PP, PUR-E, PVC

Dielectric

Yes

Color

Black and Green

Batteries Needed

None

Weight (grs)

186

Headband Style

Over-Head

Sound Amplification

No

AM/FM Radio

No

Automatic Shut-Off Function

No

Audio Input Jack

No

Hi-Visibility

No

Certifications

EU Category PPE

3

Quality Assurance

ISO 9001 / 2000

EU Certification

EU Attestation

Additional Information

User Manual

User Manual

Maintenance

Life Cycle

Cushions should be replaced periodically to retain maximum attenuation. Use the following as a guideline for replacement of ear cushions and insert foam. General use and wear - Ear cushions and foam inserts should be replaced at least every 6 months. Heavy use or wear in humid/extreme climates - Ear cushions and foam inserts should be replaced at least every 3 months. Cracking or leakage is visible - replace ear cushions and foam inserts immediately.

Storage Information

When not in use, the earmuffs should be stored in a clean dry container or locker. Do not use solvents or petroleum-based products. Do not immerse the earmuffs in water.

Care Instructions

Earmuffs are an important safety product and should be inspected regularly. Its use, care and maintenance are critical to its effective performance. Earmuffs and in particular ear cushions may deteriorate with use and should be examined at frequent intervals for cracking and leakage. If the ear cushions become hard, damaged or deteriorated, they should be replaced promptly using recommended Hygiene Kits. Earmuffs should be maintained by regular cleaning. Use a mild disinfectant solution. A gentle wipe is all that is required.

Parts & Accessories

Accessories

Hygiene Kit - Packed in a plastic bag, including two ear cushions and two foam pads. Ref. # 1010974 for T1, T1H, T1F Beltclip - For carrying purpose. Old Ref. # 1000252 New Ref. # 1016730 Cool II Pads - Sweat absorbing pads. Ref. # 1000365 5-pair, Ref. # 1000364 100-pair

Optisorb - cotton sleeve slides over earcup. Ref. # 3302101

Polar Hood - Ref. # 1016870 Lg/XLg; Ref. # 1016871 Sm/Med

Packaging

EAN Code

7312550109281

© Honeywell International Inc.